

1. Open the sms caster, click the Phone, then update All, then you can check how many ports can work, if some ports not shows proper, then you should check the sim cards or change another sim cards, when you change sim cards, you should shutdown the module, when insert sim cards, then start it.

File View Tool Help				
start serv	Receive			198.52.98.99.32719 Concurrency 0 CDR
	you	can press the update ALL t	o update the ports to check if the port read by the software	
Explorer: ×	Phone Information			
Compose				
S Contacts	🗇 Update 🚷 Update Al 🖅 Options			
Croups Groups	Phone/COM Port	Status	when it shows that , it mean the port read by the software, then you can u	use the port send sms
👝 Inbox	COM3	HDA CX11254 Soft Modern found		
👝 Outbox	MULTIBAND 900E 1800 at COM22	Upable to onen com port (uin error code: E)		
S Phone	COM24	Timeout reading COM24		
Responder	COM25	Timeout reading COM25		
Scheduler	COM26	Timeout reading COM26		
East	COM27	Timeout reading COM27		
Jen	COM28	Timeout reading COM28		
	COM :			
	Brand :			
	Model :			
	IMEI :			
	SMSC :			
	Battery :			
	Signal :			
Lindata calastad COM pa	st(c) for phone information			Licensed

2. compose for send sms ,you can input receiver number in To Numbers if you just want to send few numbers, then input the content, when you finish, then press Send to Outbox, the sms will be sent to Outbox, press the Outbox ,then you can see the detail sms list, then press the Send, they will be sent out(you should firstly choose the ports which you want to send sms).

File View Tool Help										
Send	vou can send there send the sms									
Explorer:	Compose SMS Message	l								
Compose	South Duthy 2 Bah 98 S 100 945 Total a									
Groups										
o Inbox	To Numbers: there you can input the number which you want to send to.									
Outbox	To Groups:									
Responder	Subject:									
Scheduler										
🍉 Sent	Encoding: 65M 7-bit Characters: 0 used (160 left) Options:									
	Message \$ ≧ @ > Ⅲ.# w Symbols - Variables -	í.								
	this is the content									



3. when there are lots of contact, then you can import the list from the CSV file, File>Import Contacts



It will show the Import Contacts Wizard, press Browse to choose the file which you want to import, then Next



S Import Contacts Wizard	
Step 1 of 4 - Choose File	
Choose the file you want to import your contacts from :	
C:\Users\terry\Desktop\test_import.csv	
	<u>B</u> rowse
What would you like to do with the data?	
Add to the Contacts. Any duplicate will be removed.	
Add to the Contacts. Duplicate can exist.	
Remove from the Contacts.	
< <u>B</u> ack <u>N</u> ext >	<u>C</u> ancel

It show you which row you want to start, then Next:



s Import	Contacts Wizard
Start a	Step 2 of 4 - Preview Content
1	13028860831
2	13028869832
3	13028869833
4	13028869834
5	13028869835
6	13028869836
7	13028869837
8	13028869838
9	13028869839
10	13028869840
11	13028869841
12	13028869842
13	13028869843
14	13028869844
15	13028869845
16	13028869846
17	13028869847
	< <u>Back</u> <u>Next</u> > <u>Cancel</u>

Then it will show the Arrange Fields and Columns. then Next:



 Step 3 of 4 - Arrange Fields and Columns Field Separator Comma (,) Tab Semi Colon (;) Other Field Order (Drag and move the header to rearrange them) Field Order (Drag and move the header to rearrange them) Tab Field Field Field Field Field Field Last Se 130288 	Import Co	ntacts Wizarc	I					
Field Separator • Comma (,) Tab Semi Colon (;) Other Field Order (Drag and move the header to rearrange them) Name Phone Field1 Field2 Field3 130288	ي 🔁	Step 3 o	f 4 - A	rrange	e Field	ls and	Colur	nns
• Comma (,) • Tab • Semi Colon (;) • Other Field Order (Drag and move the header to rearrange them) Name Phone Field1 Field2 Field3 Field4 Field5 Last Se 130288	-Field Separa	ator						
Field Order (Drag and move the header to rearrange them) Name Phone Field1 Field2 130288 <				color (i				
Field Order (Drag and move the header to rearrange them) Name Phone Field1 Field2 Field3 Field4 Field5 Last Se 130288 130288 130288 130288 I30288 130288 130288 130288 I30288 I30288 130288 130288 I30288 I30288 130288 130288 III III	Com	na (,) 🛛 🔘		emi Colon (;) () Ot	ner		
Name Phone Field1 Field2 Field3 Field4 Field5 Last Se 130288 130288 130288 130288 I30288 I30288 130288 130288 130288 I30288 III III	-Field Order	(Drag and mov	e the heade	r to rearran	ae them) –			
130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288	Name	Phone	Field 1	Field?	Field3	Field4	Field 5	Last Se
130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288	Nome	130288	TIERT	TICIU2	Tields	TICIGH	Tieldo	▲
130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288 130288		130288						=
130288 130288 130288 130288 130288 130288 130288 ↓ ★ Mext > Cancel		130288						
<pre> 130288 130288 130288 130288 130288 130288 130288 </pre> <pre></pre>		130288						
<pre> 130288 130288 130288 130288 130288 130288 </pre> <pre></pre>		130288						
130288 130288 130288 130288 130288 <td></td> <td>130288</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td>		130288						
130288 130288 ↓ 130288 ↓ 130288 ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓ ↓		130288						
130288		130288						
<		130288						
< Back Next > Cancel	4	130288						•
< Back Next > Cancel	•			11				4
< Back Next > Cancel								
< Back Next > Cancel								
				< P	Back	Next >		Cancel
						<u></u> exe >		<u>_</u>



🗞 Import Contacts Wizard	
Step 4 of 4 - About to Import	
Confirmation You are about to import contacts from "C:\Users\terry\Desktop\test_import.csv". It is used to add to the Contacts and any duplicate will be removed. Click "Import" to begin.	
< <u>B</u> ack <u>Import</u> <u>C</u> ancel	1

Import contacts succeeded, and show you how many contacts imported, Done

Simport Contacts Wizard	Options -	
Finished		
Result Import contacts succeeded. Imported contacts: 6462 Removed duplicates: 0		
	< <u>B</u> ack <u>D</u> one	<u>C</u> ancel



Δ.υ

How To Use SmsCaster

You can see the contact list if you import succeed.

		and enterly.									
Help											
	4										
Serie Serie	Rece	ive									
×											
nnose	Conta	icts (1	of 6462)								
tacte (6.462)	Compos	se to 🛛 🔍	New 🎭 Edit 🙈	Pelete 🛛 🔁 🗛 🛛	mport 💽	Export					
100005 (0,402)											
pubs	Name	about dita	Phone	Groups	Field1	Field2	Field3	Field4	Field5	Last Sent D.	. Sent C
xox		ntact #25	13028869832								0
itbox	<co< td=""><td>ntact #3></td><td>13028869833</td><td></td><td></td><td></td><td></td><td></td><td></td><td>-</td><td>ő</td></co<>	ntact #3>	13028869833							-	ő
ne	V 🤱 <cor< td=""><td>ntact #4></td><td>13028869834</td><td></td><td></td><td></td><td></td><td></td><td></td><td>-</td><td>0</td></cor<>	ntact #4>	13028869834							-	0
monder	🔽 💈 <cor< td=""><td>ntact #5></td><td>13028869835</td><td></td><td></td><td></td><td></td><td></td><td></td><td>-</td><td>0</td></cor<>	ntact #5>	13028869835							-	0
Jonder	🔽 🙎 <cor< td=""><td>ntact #6></td><td>13028869836</td><td></td><td></td><td></td><td></td><td></td><td></td><td>-</td><td>0</td></cor<>	ntact #6>	13028869836							-	0
eduler	🔽 💈 <cor< td=""><td>ntact #7></td><td>13028869837</td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>0</td></cor<>	ntact #7>	13028869837								0
	Col	ntact #8>	13028869838							-	0
		ntact #10>	13028869839								0
		ntact #11>	13028869841							-	0
	< Co	ntact #12>	13028869842							-	0
	V 2 <co< td=""><td>ntact #13></td><td>13028869843</td><td></td><td></td><td></td><td></td><td></td><td></td><td>-</td><td>0</td></co<>	ntact #13>	13028869843							-	0
	🗸 💈 <cor< td=""><td>ntact #14></td><td>13028869844</td><td></td><td></td><td></td><td></td><td></td><td></td><td>-</td><td>0</td></cor<>	ntact #14>	13028869844							-	0
	🔽 🔱 <coi< td=""><td>ntact #15></td><td>13028869845</td><td></td><td></td><td></td><td></td><td></td><td></td><td>-</td><td>0</td></coi<>	ntact #15>	13028869845							-	0
	🗹 🙎 <cor< td=""><td>ntact #16></td><td>13028869846</td><td></td><td></td><td></td><td></td><td></td><td></td><td>-</td><td>0</td></cor<>	ntact #16>	13028869846							-	0
	Col	ntact #17>	13028869847								0
		ntact #10>	13028869848							-	0
		ntact #20>	13028869850								0
	🗸 💈 <cor< td=""><td>ntact #21></td><td>13028869851</td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>0</td></cor<>	ntact #21>	13028869851								0
	🗸 🙎 <cor< td=""><td>ntact #22></td><td>13028869852</td><td></td><td></td><td></td><td></td><td></td><td></td><td>-</td><td>0</td></cor<>	ntact #22>	13028869852							-	0
	🔽 🙎 <cor< td=""><td>ntact #23></td><td>13028869853</td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>0</td></cor<>	ntact #23>	13028869853								0
	🖌 💈 <co< td=""><td>ntact #24></td><td>13028869854</td><td></td><td></td><td></td><td></td><td></td><td></td><td>-</td><td>0</td></co<>	ntact #24>	13028869854							-	0
	Col	ntact #25>	13028869855								0
		ntact #27>	13028869857							-	0
	<00	ntact #28>	13028869858							-	0
	V 2 <co< td=""><td>ntact #29></td><td>13028869859</td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>ő</td></co<>	ntact #29>	13028869859								ő
	🗸 💈 <cor< td=""><td>ntact #30></td><td>13028869860</td><td></td><td></td><td></td><td></td><td></td><td></td><td>-</td><td>0</td></cor<>	ntact #30>	13028869860							-	0
	🔽 🔱 <cor< td=""><td>ntact #31></td><td>13028869861</td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>0</td></cor<>	ntact #31>	13028869861								0
	🔽 🙎 <cor< td=""><td>ntact #32></td><td>13028869862</td><td></td><td></td><td></td><td></td><td></td><td></td><td>-</td><td>0</td></cor<>	ntact #32>	13028869862							-	0

If you want send same sms to all the contact, you can select All Contacts in To Group. then input the contact(you should choose the port which you want to send sms firstly before you send sms).

File View Tool Help		
Start Send	kentre	î
Explorer: ×	Compose SMS Message	
Compose	🖕 Şend to Outbox 🖉 Flight SHS 🛸 Long SHS 🖅 Dations 🗋 Clear	
Index Inbox Outbox Phone Responder Schaduler	To Bunders: To Groups: /A Contacts Subject:	•
Scheduler Sent	Encoding: GSN 7-bit Characters: 0 used (160 kH) Options:	
	Message % 💩 👩 × ≡ 🗈 🔟 🗊 Symbols - Variables -	
		~

And you can set the group, press Group>Edit. then you can see it ,you can add the number to the new group from the number which you import contacts list.



Explorer: >	Groups	an Aun Anna	
Groups Groups Outbox Outbox Phone Responder Scheduler Sent	Name	New Group Group Same: Group1 New Come Member (6451): Come Member (71):	No. of Contacts
		Inclusion Coop Services Coop Services Coop Services 100005600132 100005600132 100005600133 100005600131 100005600131 100005600131 100005600137 Inclusion Add All >> Inclusion Remove Inclusion 100005600131 Inclusion Remove Inclusion Remove Inclusion 100005600141 Inclusion Remove All <	
	Members		
	Se and a second	(No member beiongs to this group)	

You can set pause time when one sms send

File View Tool Help	
Start Send	Receive
Explorer: ×	Commence SMS Message
Explore: × Compose Compose Contacts Compose Contacts Con	Compose SMS Message Send to Outbox Pigsh SMS Long SM Option To Stroups: Options SE Subject: Image: Symbols - Variables - Message Centre Address (SMSC) Default in SIM card Message Image: Symbols - Variables - Custom St: Image: Symbols - Variables - Message Image: Symbols - Variables - Sending Speed You can set when send one sms pause some time to send another Plause Image: Second for every Image: SMS sent Plause Image: SMS sent Plause Image: SMS sent Plause Image: Second for every Image: SMS sent Plause Image: SMS sent Plause Image: SMS sent View Code + loca number image: + intl number OK Cancel

Make sure the GSM Modem have been connected to computer correctly, if that , all the ports can be found in SMS Caster, and you can set each port (SIM card) as a designated queue or default.



Explorer:	× Phone	Information				
Compose	👶 Upda	te 🕟 Update Al 🖅 Options				
	Phone,	ICOM Port	Work for Queue	Status		
Croups (3)	С 🗞 м.	ATTEAND 900E 1800 at COM3	Queue One			
xodrū 🤭	E S M.	LITEAND 900E 1800 at COM4	Queue Two			
Outbox	C 🗞 M.	LTIBAND 900E 1800 at COM5	Default Queue			
C Phone MILTERNO 90	ле 🖸 🗞 м.	LITIBAND 900E 1800 at COM6	Queue Three			
A LIGHT POLITIMED IN	🐃 💽 🕤 м.	LTIBAND 900E 1800 at COM7	Queue Four			
Responder (Enabled)	E 9 M	LITIBAND 900E 1800 at COM8	Queue Five			
Scheduler	S M.	UTIBAND 900E 1800 at COM9	Default Queue			
🤝 Sent	COM :	COM8				
	Brand :	WAVECOM MODEM				
	Model :	MULTIBAND 900E 1800				
	IMEI :	500102112125350				
	SMSC :					
	Battery :	0%				
	Signal :	Unknown				
	Queue :	Queue Five			-	
		Default Queue			bo	
		Queue One				
10-0-0-0-0-0-0-0-0-0-0-0-0-0-0-0-0-0-0-		Queue Three				
		Queue Four			2	
		Queue Five				

When you finish all these Settings, you can send text messages as your will:

1) Use a designated card send message to a designated group:

Send to	Outbox 💋 Flash SMS 💊 Long SMS 🌮 Options 📄 Clear	
To Numbers: To Groups: Sybject: Encoding : U	Default Queue Default Queue Octoue One Queue Three Queue Five Queue Five CS2 16-bit Characters: 16 used (54 left) Options: Force UCS2	-
Message 🖇	🛯 👔 🗡 🔳 ಖ 😰 Symbols - Variables -	
Have a nice	dayi	

2) Use a designated card send message to a designated number:



Compose SMS Message	
🙀 Send to Outbox 💋 Fligsh SMS 💊 Long SMS 🎦 Options 📄 Clear	
Queue : Default Queue	•
To Numbers: 12345678	
To Groups:	
Sybject:	
Encoding: UCS2 16-bit Characters: 16 used (54 left) Options: Force UCS2	
Message 💃 🏠 🏦 🗶 🔳 🍰 😰 Symbols - Variables -	
Have a nice day!	*

You can find all the messages which will be sent by different queues (SIM cards) in outbox:

Compose	Outbox (1 of 6)							
Groups (3)	Default Queue (6)					Queue Five		
Tohey	-	To	Message	Date Created	Date Sent	Status		
	101	01010101	Have a nice day!	2011/12/8 14:13:49		Wait for dispats		
Outbox (6)	Ď	11212131	Have a nice day!	2011/12/8 14:13:49		Wait for dispate		
Phone (MULTIBAND 900E		01110001	Have a nice day!	2011/12/8 14:13:49		Wait for dispate		
		10000011	Have a nice day!	2011/12/8 14:13:49		Wait for dispate		
Responder (bhabled)		11100001	Have a nice day!	2011/12/8 14:13:49		Wait for dispat		
Scheduler		10100101	Have a nice day!	2011/12/8 14:13:49	-	Wait for dispat		
Sent								
	Enc	oding : UCS2 16-bit	Characters: 16 G Subject:	used (54 left) Options :				